

AIR400-12P / AIR600-12P  
AIR400-PC-12P / AIR600-PC-12P  
AIR400S-12P / AIR600S-12P  
AIR400S-PC-12P / AIR600S-PC-12P

## Airlite / Airlite Stream Path Light 12v INSTRUCTIONS



### WARNINGS

PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE COMMENCING ANY WORK



- This is a Class 3 product (Low Voltage) – no earth required.
- **12V TRANSFORMER MAY BE REQUIRED – sold separately**
- This unit must be fitted by a competent person – if in doubt consult a qualified electrician.
- Install in accordance with IEE wiring regulations and current Building Regulations.
- To prevent electrocution, switch off mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electrical supply without your knowledge.
- This light fitting should be connected to a circuit with a 30Ma RCD fitted.
- If replacing an existing fitting, make a careful note of the connections.
- When changing the bulb, always switch off at the mains & allow the bulb to cool before handling – **LAMP WILL GET HOT WHEN IN USE.**
- All connections should be made as watertight as possible to avoid electrical shortage.
- Always use the correct type & wattage of bulb. Never exceed the wattage stated.
- The unit may get warm whilst on for a period of time.
- **The head of the product is heavy (up to 3kg) – please handle with care**

**Materials:** Anodised Aluminium & Solid Crystal Glass

**Voltage:** 12v – Low Voltage

**Max. Wattage:** 35W

**Lamp Fitting:** MR16

**Recommended Lamp:** LED

**IP Rating:** IP65

**Product Height:** 400mm or 600mm

**Sensor:** Photocell (Dusk to Dawn) OPTIONAL



**3 YEAR  
GUARANTEE**

see website for  
more details

Producer Registration Number:

WEE/KC3440XY

### RETURNS – Please contact us by phone or email

Lumena Lights Ltd  
Centre 33 Long March  
Daventry  
Northants  
NN11 4NR

Tel: +44 1327 871161  
Fax: 0800 066 4410  
Email: [sales@lumenalights.com](mailto:sales@lumenalights.com)

Full product range & more information:

[www.lumenalights.com](http://www.lumenalights.com)



## INSTALLATION:

---

- A length of 12v 2 core rubber cable is supplied with a VERSA 2 pin male plug (H05RN-F – may vary).
- Push the plug firmly into the female adaptor of the Transformer or splitter.
- Screw the attached threaded cap to the female adaptor to create a secure connection.
- If a splitter is used, ensure a waterproof cap is used to cover any unused terminals.
- Unscrew the head carefully and install MR16 bulb into the bulb holder via the guide clip (push).
- Carefully place the rubber seal between the body and head to ensure a waterproof seal and screw on head securely.

**IMPORTANT: When securing the base, do not overtighten as this could lead to fracture. Do not use high power electric socket tools.**

### NOTES:

- To ease with head / body assembly, a small amount of oil such as '3 in 1' can be applied to the neck thread.
- If the head is accidentally cross-threaded when securing to the body, turn anti-clockwise and try again – it should then screw on easily.
- Product base is fixed to the main part of the light. 4 x Anchor bolts can be used to fix the product to the relevant surface (not supplied).
- The rubber seal supplied must be installed between the head and the body and **MUST NOT** be twisted to ensure a waterproof connection.
- Photocell versions – photocell is factory pre-set and cannot be changed.
- **The head of the product is heavy (up to 3kg) – handle with care**

**Male 2 Pin Plug & Play Adaptor  
(supplied)**



**Female 2 Pin Plug & Play Adaptor**



## CLEANING:

---

Occasional cleaning and care is recommended for this product. Please refer to our website for the best way to clean different materials.

**Full VERSA Plug & Play Range & More Information:  
[www.lumenalights.com](http://www.lumenalights.com)**